

Comchip

SMD Diode Specialist

IATF16949 (AEC-Q101)



Taiwan Sales Office & Factory

No. 586, Jianguo Rd., Yingge Dist
New Taipei City 23943, Taiwan
Tel : 886-2-86776675
Fax : 886-2-86776672

USA Sales Office

4115 Clipper Court, Fremont,
CA 94538, USA
Tel : 510-6578671
Fax : 510-6578921

ESD Suppressors

Part Number	Circuit	VRWM(V)	IPP (A)	VC (V)	Cj (PF)	ESD (kV)	Package
CPDWL5V0SPC		5	2.5	14	0.3	15	01005(DFN0402)
CPDZC3VU		5	4	15	9	30	0201 (DFN0603)
CPDZC5V0HP		5	2	15	3	15	0201 (DFN0603)
CPDZC5V0C		5	2	15	0.2	15	0201 (DFN0603)
CPDZC5V0SPC		3.9	6.5,2	10.6,17.5	35,14	30,30	0201 (DFN0603)
CPDQR2V5U~3V3U		2.5,3,3	11,7	15,11	6,38	30	0402 (DFN1006)
CPDQR3V3R		3.3	2	18	18	12	0402 (DFN1006)
(A)CPDQC3V3T		3.3	17	10	25	30	0402 (DFN1006)
(A)CPDQC3V3C		3.3	17	8	6	20	0402 (DFN1006)
CPDQC3V3A(U)		3.3	4	14	0.2/0.4	20	0402 (DFN1006)
CPDQC5V0A(U)		5	4	12	0.3/0.6	20	0402 (DFN1006)
CPD(XX)5V0C		5	4	14.5	30	8	0402(DFN1006), 0503, 0603(DFN1608), 1005
(A)CPD(XX)5V0R		5	11	12	24	30	0402(DFN1006), 0603(DFN1608), 0503
(A)CPD(XX)5V0HE		5	9.4	18.6	15	30	0402(DFN1006), 0603(DFN1608)
(A)CPD(XX)5V0P		5	5	17	6	30	0402(DFN1006), SOD-523
(A)CPDQC5V0ESPC		5	4	25	0.35	25	0402 (DFN1006)
(A)CPD(XX)5V0CSP		5	3	19	0.3	15	0402(DFN1006), 0603(DFN1608)
CPD(XX)5V0USP		5	3	20	0.9	15	0402(DFN1006), 0603(DFN1608)
CPD(XX)5V0~36V		5, 12, 24, 36	5, 1, 1, 1.5	15, 25, 47, 58	20	8	0402(DFN1006), 0503, 0603(DFN1608)
(A)CPD(XX)12VE~24VE		12, 24	5, 3	23, 46	30, 13	30	0402(DFN1006), 0603(DFN1608)
(A)CPD(XX)12VEU~24VEU		12, 24	5, 2.5	22, 42	60, 35	30, 25	0402(DFN1006), 0603(DFN1608)
CPD(XX)5V0U~36VU		5, 12, 24, 36	16, 5, 3, 1	12.5, 24, 50, 58	120, 60, 35, 25	15, 30, 15, 25	0402(DFN1006), 0603(DFN1608)
CPDQR3V3~5V0UP		3.3, 5	5, 2	8, 12.5	16, 10	15, 20	0402(DFN1006), 0603(DFN1608), SOD-523
(A)CPD(XX)5V0		5	5	10	12	20	0402(DFN1006), 0503, 0603(DFN1608), 1005, SOD-523
(A)CPD(XX)5V0P		5	3	13	3	12	0402 (DFN1006), SOD-523(H)
CPD(XX)5V0U		5	16	12.5	120	15	0402(DFN1006), 0503, 0603(DFN1608), 1005, SOD-523
CPDV/H(XX)		3~24	-	-	0.8	15	SOD-323, SOD-523

ESD Suppressors Array

Part Number	VR (V)	IPP(A)	VC (V)	CT (PF)	ESD (kv)	Package
CPDT-5V0~(A)24V	5, 12, 24	5, 1, 1	15, 25, 47	15, 12, 10	8	SOT-23
CPD(XX)-5V0C	5	4	14.5	30	8	SOT-23, SOT-323
CPDT-5V0LPC	5	10	15	3	30	SOT-23
CPDT-5V0USP	5	5	25	0.8	25	SOT-23
CPDT-5V0UHP	5	17	11	1.2	15	SOT-23
CPD(XX)-5V0U	5	8	10	80	8	SOT-23, SOT-323
CPDT-12VEU	12	5	22	60	30	SOT-23
CPDT712	12	12	33	75	15	SOT-23
CPDT5-5V0U	5	8	10	80	15	SOT-23-5
CPDT6-5V0UPC	5	10	12.5	4	30	SOT-23-6
CPDT6-5V0USP	5	5	25	0.8	25	SOT-23-6
CPDT6-(XX)V4USP	5, 24	10, 25	15, 47	20, 10	16	SOT-23-6
CPD(X)5-(XX)UP	3.3, 5	5	8, 10	16, 60	15	SOT-353, SOT-553, SOT-563
CPDV6-5V0U	5	-	8	80	15	SOT-363, SOT-553
CPDVR065V0U	5	2	11	15	15	DFN1616
CPDVR083V3UA	3.3	5	8	30	15	SOT-383F
CPDVR085V0C	5	4	14.5	30	8	SOT-383F
CSRS045V0P	5	5	9	1.4	12	SOT-143
CPDA10R3V3U~5V0U	3.3, 5	5	11, 18	0.7	15	DFN10P(DFN2510)
CPDA10R5V0P	5	2	13	0.25	15	DFN10P(DFN2510)
CPDA10R5V0SP	5	1	12	0.15	15	DFN10P(DFN2510)
CPDQ03C5V0HP	45	5	5.5	3	9	0402C-03(SOT-883)

Switching Diodes

Part Number	IF (mA)	VRRM (V)	Trr (nS)	Case
CDBZC01100	100	100	4	0201(DFN0603)
CDS(XX)400(BS)	100	90	4	0402(DFN1006), 0503, 0603(DFN1608), SOD-723
1SS400	100	90	4	SOD-523
(A)CDS(XX)101A	100	80	4	0603(DFN1608), 1005
CDS(XX)355(BS)	100	80/100	4	1005
CDS(XX)4148(S)	150	75/100/150	4	0402(DFN1006), 0503, 0603(DFN1608), 1005, LL34, SOD323, DO35
(A)CDS(XX)4448	125	80~250	9	0402(DFN1006), 0503, 0603(DFN1608), 1005, SOD-123, SOT23, SOT323, SOT-523, SOT363, SOT-563
CDS(X)-19/20/21 Series	200	100~200	50	SOD-323, SOD-123, SOT-23, SOT-323, SOT-523
(A)CDST-70/99	70	200	4	SOT-23
(A)CDST-2004S	225	300	50	SOT-23
MMBD/CDSV 914 Series	200	75	4	SOT-23, SOD-323
CDSW3004	224	300	50	SOD-123
BAS521	250	300	50	SOD-523
BAS516H	250	75	4	SOD-523
CDSV6 Series	100~215	75~80	4	SOT-363
CDSH3 Series	100~300	20~200	4~50	SOT-523
CDSH6 Series	200~250	75~80	4	SOT-563
CDST Series	100~300	70~250	3~50	SOT-23
CDSV3 Series	100~300	20~200	4~50	SOT-323

Small Signal Schottky Diodes

Part Number	IF (mA)	VRRM(V)	VF (V)	IR(μA)	Case
CDB(XX)00340	30	40/45	0.37	1	0402(DFN1006), 0503, 0603(DFN1608), 1005, SOT-323, SOT-523, SOT-363, SOD-723
(A)RB751V-40	30	40	0.73	0.5	SOD-323
CDB(XX)70	70	70	0.41	0.1	0503, 0603(DFN1608), SOT-23, SOT-323, SOT363
(A)CDB(XX)0130L	100	30/35	0.35	10	0201(DFN0603), 0402(DFN1006), 0503, 0603(DFN1608), 1005
(A)CDB(XX)0130R	100	30/35	0.46	0.5	0201(DFN0603), 0402(DFN1006), 0503, 0603(DFN1608), 1005
CDB(XX)0130	100	30	0.44	100	0603(DFN1608), 1005
CDB(XX)0140(L)	100	40	0.34	10	0402(DFN1006), 0503, 0603(DFN1608), 1005, SOD-323
CDB(XX)0140R	100	40	0.45	10	0402(DFN1006), 0503, 0603(DFN1608), 1005
CDB(XX)0145	100	45	0.55	100	0603(DFN1608)
CDB(XX)0230R	200	30	0.60	200	0201(DFN0603), 0402(DFN1006), 0503, 0603(DFN1608), 1005
CDBW46-G	150	100	1	2	SOD-123
CDBURT0230LL	200	30	0.39	200	0603(DFN1608)
CDB(XX)0230L	200	30	0.50	200	0402(DFN1006), 0503, 0603(DFN1608), 1005
CDB(XX)0230R	200	35	0.60	1	0201(DFN0603), 0402(DFN1006), 0503, 0603(DFN1608)
(A)CDB(XX)0230	200	30	0.50	200	0603(DFN1608), 1005, SOD-523
CDB(XX)42	200	30	0.40	10	0402(DFN1006), 0503, 0603(DFN1608), 1005
CDB(XX)43	200	30	0.45	15	0402(DFN1006), 0503, 0603(DFN1608), 1005
CDB(XX)54 Series BAT54x Series	200	30	1.00	100	0402(DFN1006), 0503, 0603(DFN1608), 1005, SOT-23, SOT-323, SOT-523, SOT-363
CDB(XX)0240L	200	40	0.48	200	0402(DFN1006)
CDB(XX)0240LR	200	40	0.58	200	0402(DFN1006)
CDB(XX)0240	200	45	0.55	200	0603(DFN1608), 1005
CDB(XX)40 Series	200	40	1.00	40	0402(DFN1006), 0503, 0603(DFN1608), 1005, SOT-23, SOT-323
CDB(XX)0245	200	45	0.55	200	0603(DFN1608), 1005
CDBFR03100	300	100	0.82	50	1005
CDB(XX)0320~0340	350	20~40	0.6	200	0603(DFN1608), 1005
CDB(XX)0520~0530	500	20~30	0.36	100	0603(DFN1608), 1005, SOD-123
CDB(XX)0520L	500	20	0.30	100	1005, SOD-123
CDB(XX)0530L/LL	500	30	0.34	100	0402(DFN1006), 0603(DFN1608)
RB551V-30	500	30	0.47	100	SOD-323
(A)CDB(XX)0540	500	40	0.51	500	0603(UC), 0603(URT)

SMD Schottky Diodes

Part Number	IF (A)	VRRM(V)	VF (V)	Case
CDBQT140	1	40	0.61	0402/DFN1008
CDBVL(X)40	1,2	40	0.5/0.58	0603/DFN1608
CDBUC140LC	1	40	0.6	0603(DFN1608)
CDBFN140~160	1	40/60	0.55/0.7	SOD-323
CDBV120~1100	1	20/40/100	0.75/0.9/0.82	SOD-323
CDBM(X)1XX	1	20~200	0.35~0.83	SOD-123 Series
CDBM140L	1	40	0.38	SOD-123
(A)CDBMT140~1200	1	40~200	0.5~0.92	SOT-123H
CDBM140LR	1	40	0.45	SOD-123F
CDBW120-140	1	20~40	0.75~0.9	SOD-123
(A)CDBA140~1200	1	40~200	0.5~0.9	SMA
(A)CDBA1100LR	1	100	0.75	SMA
SS14~120	1	40~200	0.55~0.9	SMA
CDBA140L	1	40	0.38	SMA
CDBA140LL	1	40	0.34	SMA
CDBA140SL	1	40	0.31	SMA
CDBAS140	1	40	0.50	SMA-S
CDBB140~1200	1	40~200	0.5~0.9	SMB
CDBB140LR~1200LR	1	40~200	0.45~0.85	SMB
CDBVF240	2	40	0.48	SOD-323
CDBM(X)220~2200	2	20~200	0.52~0.92	SOD-123 Series
SS24~220	2	40~200	0.4~0.95	SMA
(A)CDBA240~2200	2	40~200	0.50~0.90	SMA
CDBA240L	2	40	0.40	SMA
CDBA240LL	2	40	0.35	SMA
(A)CDBA240LR~2200LR	2	40~200	0.45~0.85	SMA
(A)CDBB240~2200	2	40~200	0.50~0.90	SMB
CDBB240LR~2200LR	2	20~200	0.45~0.85	SMB
CDBC220LR~2200LR	2	20~200	0.40~0.85	SMC
(A)CDBM(X)340~3100	3	40~100	0.54~0.85	SOD-123 Series
(A)CDBA340~3200	3	40~200	0.5~0.9	SMA
SS34~320	3	20~200	0.55~0.95	SMA
CDBA340LR~3200LR	3	40~200	0.45~0.85	SMA
CDBAS340(L)	3	40	0.5/0.4	SMA-S
(A)CDBB340~3200	3	20~200	0.5~0.9	SMB
SS32B~320B	3	20~200	0.44~0.95	SMB
CDBB340LR~3200LR	3	40~200	0.45~0.85	SMB
(A)CDBC320~3200	3	20~200	0.45~0.90	SMC
CDBC320LR~3200LR	3	40~200	0.45~0.85	SMC
(A)CDBA540 ~5200	5	40~200	0.55~0.90	SMA
CDBAS540	5	40	0.55	SMA-S
(A)CDBB540~5200	5	40~200	0.55~0.87	SMB
CDBC520~5200	5	40~200	0.55~0.90	SMC
CDBD540~5200	5	40~200	0.55~0.92	TO-252
CDBD640	6	40	0.57	TO-252
CDBD840	8	40	0.57	TO-252
CDBD1040~10200	10	40	0.55~1.00	D2PAK
CDBHA10120	10	120	0.74	TO-277
CDBD3080	30	60	0.70	D2PAK

General Purpose Rectifiers

Part Number	IO (A)	VR (V)	Case
CGRV01J	1	1000	SOD-323
(A)CDGRTS4001~4007	1	50~1000	TS/SOD-123FL
(A)CGRKM4001~4007	1	50~1000	SOD-123F
(A)S1D~(A)S1M	1	50~1000	SMA
S1T~S1Y	1	1200~2000	SMA
1N4001~4007	1	50~1000	DO-41
S2T~S2Y	1.5	1300~2000	SMB
(A)CGRB201~207	2	50~1000	SMB
(A)CGRB301~307	3	50~1000	SMB
(A)CGRC301~307	3	50~1000	SMC
S3T~S3Y	3	1300~2000	SMC
1N5400~5408	3	50~1000	DO-201AD
CGRC501~507	5	50~1000	SMC
8A005~10/S	6	50~1000	R8/DO-201AD
CGR860T	8	600	TO-220AC

Fast Recovery Rectifiers

Part Number	IO (A)	VR (V)	Trr (nS)	Case
CFRM(T)104~107	1	400~1000	150~500	MINI SMA, SOD-123H
CFRA101~107	1	50~1000	150~500	SMA
FR101~107	1	50~1000	150~500	DO-41
CFRA201~207	2	50~1000	150~500	SMA
CFRB201~207	2	50~1000	150~500	SMB
FR201~207G	2	50~1000	150~500	DO-15
CFRC301~307	3	50~1000	150~500	SMC
FR601~207G	6	50~1000	150~500	R6

Super Fast & Ultra Fast Recovery Rectifiers

Part Number	IO (A)	VR (V)	Trr (nS)	Case
CURM(T)103~107	1	200~1000	50~75	MINI SMA, SOD-123H
(A)CURA101~107	1	50~1000	50~75	SMA
UF4001~4007	1	50~1000	50~75	DO-41
HER101~108G	1	50~1000	50~75	DO-41
(A)CSFA102~104	1	100~600	35~50	SMA
CSFM(X)103~105	1	200~600	35	MINI SMA, SOD-123(X)
CSFMT104~108	1	200~600	35	SOD-123H
(A)CEFM101~105	1	50~600	25	MINI SMA
(A)CURB201~207	2	50~1000	50~75	SMB
HER201~208G	2	50~1000	50~75	DO-15
CSFB201~205	2	50~600	35	SMB
(A)CURB301~307	3	50~1000	50~75	SMB
(A)CSFB304~308	3	200~600	35	SMB
CSFC304~308	3	50~400	35	SMC
ACEFC304	3	200	20	SMC
CURC301~307	3	50~1000	50~75	SMC
UF3001~3008	3	50~1000	50~75	DO-201AD
CEFC403	4	200	25	SMC
SF51~SF56	5	50~400	35~40	DO-201AD
CUR801~808	8	50~1000	60	TO-220AC
SF1010~1060	10	50~600	35	ITO-220AB

Part Number	TYPE	PD(W)	VDS(V)	ID(A)	VGS(V)	RDS(ON)(mΩ)@VGS=4.5V	Package
CEH2313	P	1.6	-30	-5.2	20	75	TSOP-6
CEM3053	P	3.1	-30	-15	25	18	SOP-8
CEZ6R86L	P	83	60	56	20	9.6	PDFN5x6
CJM1206	P	0.25	-12	-6	8	45	DFNWB2*2-6L-J
CJS8810	Dual N	0.7	20	7	12	22	TSSOP8
CMS05P03G6	P	1.6	-30	-5.2	20	75	TSOP-6
CMS05P03Q8	P	2.5	-30	-5.3	25	60	SOP-8
CMS06N10V8	N	10.4	100	6.8	20	115	PDFN 3.3x3.3
CMS06NP03Q8	N+P	1.5	30	-	20	42	SOP-8
CMS06PP03Q8	Dual P	1.5	-30	-6	20	82	SOP-8
CMS07NP03Q8	N	1.5	30	-	20	42	SOP-8
CMS07P03Q8	P	2.5	-30	-7.5	20	32	SOP-8
CMS10N03Q8	N	3.1	30	10.2	20	29	SOP-8
CMS10N10Q8	N	2.5	100	28	20	28.5	SOP-8
CMS11N10Q8	N	3.1	100	11	20	17	SOP-8
CMS13N08H8	N	83	60	56	20	9.6	PDFN5x6
CMS15P03Q8	P	3.1	-30	-15	25	18	SOP-8
CMS15P03Q8A	P	4.5	-30	-15	20	20	SOP-8
CMS16N06D	N	27	60	16	20	60	D-PAK/TO-252
CMS16P06D	P	25	-60	-16	20	65	D-PAK/TO-252
CMS16P06H8	P	2	-60	-16	20	65	PDFN5x6
CMS2010	N	1.5	20	7	12	18	TSSOP8
CMS23P04D	P	31.3	-40	-23	20	65	D-PAK/TO-252
CMS25N03Q8	N	2.5	30	25	20	6	SOP-8
CMS25N03V8	N	20	30	25	20	28	PDFN 3.3x3.3
CMS25N10D	N	60	100	25	20	50	D-PAK/TO-252
CMS25NN03V8	Dual N	20.8	30	25	20	30	PDFN 3.3x3.3
CMS30N10V8	N	31.3	100	30	20	28	PDFN 3.3x3.3
CMS3134KQA	N	0.1	20	0.75	12	380	WBFBP-03E
CMS3139KQA	P	0.1	-20	-0.66	12	520	WBFBP-03E
CMS32P03V8	P	29	-30	-7.7	20	32	PDFN 3.3x3.3
CMS3586A6	N+P	1.38	14	5/-3.3	12	40	DFN2X2-6L
CMS3588A6	N+P	1.38	14	6/-4	8	26	DFN2X2-6L
CMS35N04V8	N	44	40	35	20	13.5	PDFN 3.3x3.3
CMS35P03D	P	34	-30	-35	20	35	D-PAK/TO-252
CMS40N03V8	N	52	30	25	20	5.8	PDFN 3.3x3.3
CMS42N08V8	N	52	60	42	20	15	PDFN 3.3x3.3
CMS42N10H8	N	83.3	100	42	20	28.5	PDFN5x6
CMS42P03V8	P	37	-30	-42	20	25	TSOP-6
CMS45P03H8	P	2	-30	-45	20	25	PDFN5x6
CMS50N10D	N	130	100	50	20	-	D-PAK/TO-252
CMS50P04D	P	2.5	-40	-11	20	18	D-PAK/TO-252
CMS70N04H8	N	2	40	70	20	12	TSOP-6
CMS80N06D	N	83	60	80	20	-	D-PAK/TO-252
CMSBN4612	Dual N	1.4	22	6	12	36	CSPB1313-4
CMSBN4615	Dual N	1.5	20	7	12	26	CSPB1515-4
CMSBN4616	Dual N	1.5	15	8	12	18	CSPB1515-4
CMSBN6801	Dual N	2	20	13	12	11.5	CSPB2718-6
CMS0103M	N	1.5	100	3	20	-	SOT-89-3L
CJA03N10	N	0.5	100	3	20	170	SOT-89-3L

Bridge Diodes

Part Number	IO (A)	VR (V)	Case
B05S~B10S	0.8	50~1000	MBS
DB101~DB107	1	50~1000	DB
DB101S~DB107S	1	50~1000	DBS
ABS05~ABS10	1	50~1000	ABS
DF06S~DF10S	1	600~1000	DFS
DF005~DF10	1	600~1000	DF
CDBHD140L~CDBHD1100L	1	40~100	TO-269AA(MDS)
DF1505S~DF1510S	1.5	50~1000	DFS
DF2005~DF210	2	50~1000	DF
DF2005S~DF210S	2	50~1000	DFS
KBP2005G~KBP210G	2	50~1000	KBP
CDBHD240~CDBHD2100	2	40~100	TO-269AA(MDS)
CDBHM220L~CDBHM2100L	2	20~100	MBS-2
CSPB30K/M	3	800/1000	SPB
CSPB40K/M	4	800/1000	SPB
GBL005~GBL10	4	50~1000	2GBJ
GBU4005~GBU410	4	50~1000	GBU
KBL4005~KBL410	4	50~1000	KBL
CSPB60K	6	800	SPB
GBU6005~GBU610	6	50~1000	GBU
KBU6005~KBU610	6	50~1000	KBU
GBU8005~GBU810	8	50~1000	GBU
KBU8005~KBU810	8	50~1000	KBU
GBU10005~GBU1010	10	50~1000	GBU
KBU10005~KBU1010	10	50~1000	KBU
MP10005G~MP1010G	10	50~1000	MP8
GBU15005~GBU1510	15	50~1000	GBU
GBJ25005~GBJ2510	25	50~1000	GBJ
SR3030PT~SR30150PT	30	30~1000	TO-3P
KBU35005~KBU3510	35	50~1000	KBU
BR5005L~BR5010L	50	50~1000	BR-L
KBPC10005~KBPC5010	10~50	50~1000	KBPC
KBPC10005W~KBPC5010W	10~50	50~1000	KBPC-W

Zener Diodes

Part Number	VZ (V)	(%)	PD (mW)	Case
CZR(XX)52C2~39	2.0~39	5	125	0201(DFN0603), 0402(DFN1006), 0503, 0603(DFN1608), 1005
CZR(XX)2V4B~39VB	2.4~39	2.5	125	0402(DFN1006), 0503, 0603(DFN1608), 1005
CZRW4678~4717	1.8~43	5	350	SOD-123
(A)CZRW5223B~5256B	2.7~30	5	350	SOD-123
CZRW55C2V4~39	2.4~39	5	500	SOD-123
(A)CZRW5223B~5256B	2.4~56	5	500	SOD-123F
CZMF4734A~CZMF1330	5.6~330	5	1000	SMF
(A)CZRV52B2V4~39	2.4~39	2	200	SOD-323
(A)CZRV5223B~5256B	2.4~51	5	200	SOD-323
(A)CZRH584C2V4~C51	2.4~51	5	200	SOD-523
CZRT23C2V7~23C39	2.7~39	5	300	SOT-23
(A)CZRT-55C2V4~75	2.4~39	5	350	SOT-23
CZRV3-55C2V4~39	2.4~39	5	200	SOT-323
CZRH3-55C2V4~39	2.4~39	5	150	SOT-523
(A)CZRA4728~4764	3.3~100	5	1000	SMA
CZRA1100B~1330B	110~330	5	1000	SMA
CZRA5920B~5956B	6.2~200	5	1500	SMA
CZRB3005~3200	6.2~200	5	3000	SMB
(A)CZRC5340B~5388B	6~200	5	5000	SMC

TVS Diodes

Part Number	VR (V)	PD (W)	Package
TV02W Series	5.0~190	200	SOD-123
(A)TV04A Series	5.0~440	400	SMA
(A)P4KE Series	6.8~600	400	DO-41
TV05A Series	5.0~190	500	SMA
SA Series	5.0~190	500	DO-15
ASMAJ Series	5.0~440	400	SMA
TV06A Series	5.0~58	600	SMA
ATV06A Series	13~40	600	SMA
(A)TV06B Series	5.0~440	600	SMB
ASMBJ Series	5.0~440	600	SMB
P6KE Series	6.8~600	600	DO-15
TVJ10B Series	5.0~43	1000	SMB
(A)TV15C Series	5.0~440	1500	SMC
ASMCJ Series	5.0~440	1500	SMC
1.5KPA Series	5.0~440	1500	DO-201AD
(A)TV30C Series	5.0~440	3000	SMC
3KP Series	5.0~440	3000	R-6
ATV36SM5 Series	10~43	3600	DO-218AB
ATV46SM5 Series	10~43	4600	DO-218AB
(A)TV50C Series	11~440	5000	SMC
(A)5KP Series	5.0~440	5000	R-6
ATV66AM8 Series	10~43	6600	DO-218AB
15KP Series	17~280	15000	R-6

MOSFET

Part Number	TYPE	PD(W)	VDS(V)	ID(A)	VGS(V)	Package
2N7002	N	0.35	60	0.25	-	SOT-23
2N7002K	N	0.225	60	0.115	20	SOT-23
2N7002KDW	N	0.15	60	0.34	20	SOT-363
2N7002T	N	0.15	60	0.115	20	SOT-523
2N7002W	N	0.2	60	0.115	20	SOT-323
BSS123T	N	0.3	100	0.19	20	SOT-23
BSS138	N	0.35	50	0.22	20	SOT-23
BSS138W	N	0.2	50	0.2	20	SOT-323
BSS84	P	0.225	-50	-0.13	20	SOT-23
BSS84W	P	0.2	-50	-0.13	20	SOT-323
CJ1012	N	0.275	20	0.5	12	SOT-523
CJ2101	P	0.29	-20	-1.4	8	SOT-323
CJ2301	P	0.4	-20	-2.3	8	SOT-23
CJ2324	N	0.35	100	2	20	SOT-23
CJ3134K	N	0.15	20	0.75	12	SOT-723
CJ3139KDW	Dual P	0.15	-20	-0.66	12	SOT-363
CJ3400	N	0.35	30	5.8	12	SOT-23
CJ3401	P	0.35	-30	-4.2	12	SOT-23
CJ3404	N	0.35	30	5.8	20	SOT-23
CJ3415	P	0.35	-20	-4	8	SOT-23
CJX3134K	N	0.15	20	0.75	12	SOT-563
CJX3139K	P	0.15	-20	-0.66	12	SOT-563
CMS0102	N	1.25	100	2	20	SOT-23
CMS02N06KT	N	1.38	60	2.2	20	SOT-23
CMS02P02T6	P	1.25	-20	-2.5	10	SOT-26
CMS02P06T6	P	1.1	-60	-2.4	20	SOT-26
CMS04N06Y	N	3.1	60	4	20	SOT-223
CMS2101	P	0.29	-20	-1.4	8	SOT-323
CMS2302	N	1	20	3.6	12	SOT-23
CMS2305A	P	1.38	-30	-3.2	12	SOT-23
CMS3407T	P	1.38	-30	-4.1	20	SOT-23
CMSN1012H3	N	0.15	20	0.56	8	SOT-523
CMSP1013V3	P	3.5	-20	-0.54	10	SOT-323
CMSP3413T	P	1.38	-20	0.49	12	SOT-23